



FEATURES:

**Single Phase Open Frame Double Cylinders Gasoline Generator, Powered by NSM Alternator
Ideal for Charging T-40 and T-30 Agricultural Spraying Drones**



OHV
Over Head Valve Easy To Maintenance



AVR
AVR Is a Device Often Solid State, For Controlling The Output Voltage of a Generator



Wheel Transport System



Single Plug
Possible To Getting A Full Load From A Single Plug (63 A)



Choke System
When The Cold Weather, Choke System Aid To Operate The Engine.



Dual Element Air Filter
Dual-Element Air Filter That Purifies The Sucked Air From Dust And Dirt

Generator		Engine		Size	
Standby Power	16.5 kVA	Model	QST2V80FE	Weight	150 kg
Prime Power	15 kVA	Max. Output Power	28 hp / 20.7 kw	Width	600 mm
Continues Rated Current	65.25 A	Rotation Speed	3000 / 3600 r/min	Length	900 mm
Dc Output	8.3 A / 12v	Cooling System	Air-Cooled	Height	900 mm
Starting System	Electrical Start	Ignition System	TCI		
Rated Voltage	220 V	Oil Type	10-30 or 15-40		
Fuel Type	Gasoline	Fuel Tank Capacity	20 L		
Number of Phases	Single Phase	Bore×Stroke	80 x 74 mm		
Noise Level	74 Db	Displacement	743 mm		
Continuous Operating Time	12 H	Lubrication oil capacity	1.7 L		
Rated Frequency	50 Hz	Engine Type	2 Cylinder, 4Stroke, OHV, Gasoline Engine		
Power Factor (cosφ)	1.0 / 0.8				

Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

Standby Power

The maxpower available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utilitypower outage or under test conditions for up to 200 hrs of operation per year under average of 70%load.Overloading isn't permissible.

Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.